
SOLAR INVERTER IVPS Series

Upgrade system, Stronger protection



Product Advantages

- Bypass charging function, AC charge available When the unit off.
- 90-280V AC Wide input voltage.
- Grid electricity and battery power priority is optional.
- Higher charging current and adjustable
- Communicate with our MPPT charge controller.
- Intelligent protection, higher class of security.



PRODUCT PARAMETERS

			IVPS1	0048				
10000VA								
220Vac								
90Vac±7Vac								
100Vac±7Vac								
280Vac±7Vac								
270Vac±7Vac								
Security parties All								
Enthodologie Podencente de								
3)								
·								
			6,	3A				
			220)Vac				
90~280Vac								
troller is enti-	onal\							
troller is option		_	_				_	
_								
	2000			C11-5.				
	3000	500.00	50307	0.00	5,554	90-01		
_		1992					-	
-	* -	-	-	-	_	-	-	
			Pure si	ne wave				
900 - 200 -								
Secretarian resource secretaria secretaria de la constanta de								
Yes								
		Yes						
			0320	231///61/				
	اممط	< 500/ 11 E	11.5V/2	23V/46V	NO/- 11\//22\	1/11/1		
			11.5V/2 V/23V/46V	/ Load≥5	0%,11V/22\ 50%,11.5V/2			
	troller is opti	troller is optional)	Depend troller is optional)	1000 8000 48 Sinusoidal(Util 220 90Vac 100Va 280Va 270Va 280° 50Hz As same as ir Air switch Air switch Air switch 15ms (15ms (15ms (0A- Circuit 6 Depends on battery Y troller is optional)	8000W 48V Sinusoidal(Utility or general 220Vac 90Vac±7Vac 100Vac±7Vac 100Vac±7Vac 280Vac±7Vac 280Vrms 50Hz/60Hz As same as input waveford Air switch protection Air switch protection Air switch protection Air switch protection 15ms (typical) 15ms (typical) No 63A 220Vac 90~280Vac Dependent on battery type 80A 0A~80A Circuit breaker 63A Depends on battery type or Selft Yes troller is optional)	10000VA 8000W 48V Sinusoidal(Utility or generator) 220Vac 90Vac±7Vac 100Vac±7Vac 280Vac±7Vac 280Vrac±7Vac 280Vrms 50Hz/60Hz As same as input waveform Air switch protection Air switch protection ≥95% (Rated R load, and battery is fully charged) 15ms (typical) No 63A 220Vac 90~280Vac 90~280Vac Dependent on battery type 80A 0A~80A Circuit breaker 63A Depends on battery type or Self-defined Yes troller is optional)	10000VA 8000W 48V Sinusoidal(Utility or generator) 220Vac 90Vac±7Vac 100Vac±7Vac 280Vac±7Vac 280Vrms 50Hz/60Hz As same as input waveform Air switch protection Air switch protection ≥95% (Rated R load, and battery is fully charged) 15ms (typical) 15ms (typical) No 63A 220Vac 90~280Vac Dependent on battery type 80A 0A~80A Circuit breaker 63A Depends on battery type or Self-defined Yes troller is optional) • • • • • • • • • • • • • • • • • • •	

